

CM Pro eXtra

Engage with your audience around the clock with the CM Pro eXtra

Our 24/7 playout screen which comes with CleverLive digital signage

Available in a range of sizes
32" | 55" | 65" | 86"



Operational
24/7

Screen
Sustainability
Scheduling
for reduced power
consumption

CLEVER[®] LIVE

Subscription free feature rich digital signage.

Create your account today at cleverlive.com

1-year MDM* included
Remote access to manage, view and support your display for the ultimate in control and flexibility.


Key Features



4k Ultra HD Resolution
(55", 65", 86" only)



24/7 Usage



Landscape & Portrait



One Touch Messaging & Broadcasting



Screen Sustainability Scheduling Power Management



Control Integration



Digital Signage Full Screen Posters + Videos



Android Technology



MDM Built-in Management Control



OTA Updates & Cloud Accounts

Upgrade your solution



Add a PICO XI or PRO V4 media player for multizoned digital signage, or add an OPS or Video Conferencing Bar to create a Microsoft Teams Room or Zoom Room environment.

partnered with

logitech



CM Pro eXtra Specifications

Panel	
Screen size	32" 55" 65" 86"
Backlight Type	D-DLED
Panel Type	IPS
Brightness (Typical)	32" 450cd/m2
	55" & 65" 500 cd/m2
	86" 400 cd/m2
Native Resolution	32" 1920 x 1080 (FHD)
	55" & 65" 3840 x 2160 (UHD)
Contrast Ratio (Typical)	32" 3000:1
	55", 65", 86" 1200:1
Dynamic Contrast	32" 45000:1
	55", 65", 86" 50000:1
Panel Lifetime (Minimum)	50,000Hr
Response Time (Typical)	32" 9.5 ms
Viewing Angle	55", 65", 86" 8 ms
	178 Vertical, 178 Horizontal
Colour Value	32" 16.7M
	55", 65", 86" 1.07B (8-Bit + FRC)
Screen Treatment	3H
Haze Level	32" 3%
	55", 65", 86" 1%
Refresh Rate	60Hz
Orientation	Landscape and Portrait
Operation Hours	24/7
Area of Usage	Indoor

Mainboard	
Android Option	400vs: Android 9.0
Android CPU	4xCA55
Android GPU	MaliG31mp2
Android RAM	2GB DDR4- 2666Mhz
Android Storage	16GB eMMC
Scan Rate	200Hz

Features	
Main	Built in Digital Signage playback with alert auto source switching, Remote MDM (*MDM designed for remote support and app updating), Power Scheduler, Active Standby (HDMI Wakeup), HDMI CEC, USB Autoplay, Panel Lock, Pixel Shift, External Control, Real Time Clock (RTC)
Mechanical	32" Joystick Control, IR sensor Cable, Detachable Power Cable 55", 65", 86" Joystick Control, IR sensor Cable, OPS module slot, Secure USB cover, Detachable Power Cable
Speaker	32" 2x6 W 55", 65", 86" 2x10 W

Connectivity	
HDMI-In	32" 2xHDMI2.0 55", 65", 86" 4xHDMI2.0
HDMI-Out	x1
USB2.0	x1
USB3.0	x1
Internal USB	32" N/A
	55", 65", 86" x1
OPS	32" N/A
Audio In	32" N/A
	55", 65", 86" Line In L/R
Audio Out	32" N/A
	55", 65", 86" Headphone, SPDIF
Micro SD	32" N/A
	55", 65", 86" x1
RS232	3.5mm Jack
LAN	10/100/1000 Mbps
WiFi	2.4GHz and 5GHz
RJ12	For Service

Mechanical	
Product Dimensions	32" 734 x 78 x 435mm 55" 1236 x 83 x 709mm 65" 1456 x 96 x 834mm 86" 1962.30 x 1133 x 92.5mm
	Packaging Dimensions
Product Weight	32" 795 x 128 x 530mm
	55" 1369 x 165 x 874mm
Packed Weight	65" 1650 x 190 x 997mm
	86" 2163 x 380 x 1490mm
VESA Mounting	32" 10.5 kg
	55" 18.1kg
Bezel Width	65" 24.4kg
	86" 62kg
Bezel Width	32" 14.3 kg
	55" 23.3kg
Bezel Width	65" 31.3kg
	86" 83kg
Bezel Width	32" 200 mm(W) x 200 mm(H) M6
	55" 400mm (W) x 400mm (H) M6
Bezel Width	65" 600mm (W) x 400mm (H) M6
	86" 800mm (W) x 600mm (H) - M8
Bezel Width	32" 6/6/6/9 mm
	55" 9/9/9/11mm
Bezel Width	65" 10/10/10/14mm
	86" 25mm

Power	
Supply	110v AC - 240v AC 50/60Hz
Power Consumption (Typical)	32" 42W
	55" 138 (W) Typical/180 (W) MAX
	65" 194 (W) Typical/220 (W) MAX
Deep Standby	86" 385 (W) Typical/400 (W) Max
	≤0.5 W

CM Pro eXtra Specifications

Environmental Conditions

Operating Temperature	0-40 °C
Operating Humidity	10-90%

Accessory

Standard	QSG, Power cable, IR extender cable, Remote Control, 2 x AAA Battery
-----------------	--

Installation

The installation of this product should be completed by a qualified installer. Use of components not supplied by Clevertouch or not meeting minimum specifications may impact performance, safety and warranty. For more information, visit clevertouch.com

Warranty

Warranty term and upgrade options vary by region. Contact your local reseller or distributor for information and visit clevertouch.com/about/warranty

Compliance & Certification

Regulatory Certification	
---------------------------------	---

Support

For all Clevertouch products, visit: support.clevertouch.com

Statement

Size and weight vary by configuration and manufacturing process, please refer to the actual product. The product images are for illustrative purposes only and may slightly differ in appearance, colour, size, etc. from the actual product. The description, illustrations, etc. in this document may subject to change in accordance with the latest product specification and performance. Should the above-mentioned change in the document become necessary, the document may be updated without written notice.